

SENWA

**Senwa Mobile
S406**

Slim Qwerty with Analog TV: S406



Function	Description
Networks/bands	Networks: GSM/GPRS
	GSM : 850/1900
OS	Nucleus
Processor	MTK 6250
Display	2.0" – QCIF (176*220)
Cameras	Rear - 2.0Mpix
TV	Yes - Analog
Memory	128Mb NAND + 64Mb Ram
Memory Expansion	Micro SD up to 32GB
Phonebook	300 entries + SIM
Bluetooth	Yes (2.0)
Wi-Fi	Yes (802.11 b/g/n.11)
USB Storage	5 pin Micro connector for Storage
STBY /Talk	230h / 4h
Dimension	102.3*57*8.5mm
Weight (g)	~ 80 g
Battery	650mAH

Slim Qwerty with Analog TV: S406



Function	Description
Audio Player	MP3
Video	AVI, MP4, 3GP
Browser	WAP 2.0, Opera
Java	MIDP 2.0
Games	1 games
Social Network Apps	Twitter, Facebook,
Additional apps	World clock, Calculator, calendar, unit converter,
Alert	MP3, Midi and Vibrator
FM Radio	87.5MHz—108MHz
Speakers	single
Antennas	Internal Multimode Antenna, 2.4G antenna BT, Wi-Fi, Ext./Int. FM antenna
Buttons	Qwerty 37, 2 Softkeys, 5-direction navigation key, talk, end/power
Earphone/Jack	3.5mm connector
Charging Port	Micro USB 5pin
Sim Card	Mini (25mmX15mm)
Charger	Input: 100-240V, 50/60Hz, 0.2A; Output: 5.0V, 400mA
Contents	Phone, Battery, Charger, USB Charger/Cable, headset, User Guide

Slim Qwerty with Analog TV: S406





Thank You ...